

https://www.phoenixcontact.com/us/products/1884885



Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Contact insert, Range of articles: VARIOCON, color: light grey, number of positions: 8, rated voltage: 160, rated current: 10 A, Connection method: PCB connection, Connectors may only be connected/disconnected when under no load.

## Your advantages

- Proven COMBICON technology
- · Direct PCB connection
- · Can be keyed to prevent incorrect connection

### Commercial data

Item number	1884885
Packing unit	50 pc
Minimum order quantity	1 pc
Sales key	AB01
Product key	ABLACA
GTIN	4017918170769
Weight per piece (including packing)	5.38 g
Weight per piece (excluding packing)	4.823 g
Customs tariff number	85369010
Country of origin	PL

1884885

https://www.phoenixcontact.com/us/products/1884885



## Technical data

### Notes

otes	
General	Connectors may only be connected/disconnected when under no load.
Safety note	
Safety note	WARNING: The connectors may not be plugged in or disconnected under load. Ignoring the warning or improper use may damage persons and/or property.
	<ul> <li>WARNING: Commission properly functioning products only.</li> <li>The products must be regularly inspected for damage.</li> <li>Decommission defective products immediately. Replace damaged products. Repairs are not possible.</li> </ul>
	<ul> <li>WARNING: Only electrically qualified personnel may install and operate the product. They must observe the following safety notes. The qualified personnel must be familiar with the basics of electrical engineering. They must be able to recognize and prevent danger. The relevant symbol on the packaging indicates that only personnel familiar with electrical engineering are allowed to install and operate the product.</li> </ul>
	<ul> <li>The products are suitable for applications in plant, controller, and electrical device engineering.</li> </ul>
	<ul> <li>When operating the connectors in outdoor applications, they must be separately protected against environmental influences.</li> </ul>
	<ul> <li>Assembled products may not be manipulated or improperly opened.</li> </ul>
	<ul> <li>Only use mating connectors that are specified in the technical data of the standards listed (e.g. the ones listed in the product accessories online at phoenixcontact.com/products).</li> </ul>
	<ul> <li>When using the product in direct connection with third-party manufacturers, the user is responsible.</li> </ul>
	<ul> <li>For operating voltages &gt; 50 V AC, conductive connector housings must be grounded</li> </ul>
	<ul> <li>Ensure that the protective or functional ground has been properly connected.</li> </ul>
	<ul> <li>VDE 0100/1.97 § 411.1.3.2 and DIN EN 60 204/11.98 § 14.1.3 are applicable when combining several circuits in a cable and/or connector</li> </ul>
	Observe the corresponding technical data. You will find information:  o On the product o On the packing label o In the supplied documentation o Online at phoenixcontact.com/products under the product
	Only use tools recommended by Phoenix Contact
	<ul> <li>The installation notes/Design In documents online on the download page at phoenixcontact.com/products must be observed for this product.</li> </ul>
	<ul> <li>Use a protective cap to protect connectors that are not in use.</li> <li>The suitable accessories are available online in the accessory section of the product at phoenixcontact.com/products</li> </ul>

• Operate the connector only when it is fully plugged in.



https://www.phoenixcontact.com/us/products/1884885



• Ensure that when laying the cable, the tensile load on the connectors does not exceed the upper limit specified in the standards.
Observe the minimum bending radius of the cable. Lay the cable without twisting it.
• The connector warms up in normal operation. Depending on the ambient conditions, the surface of the connector can continue to warm up. In this case, the user is responsible for posting warnings (e.g. DIN EN ISO 13732-1:2008-12).

### Product properties

Product type	Contact insert
Product family	VARIOCON
Series	VC-M
Number of positions	8
Number of module slots	1

#### Insulation characteristics

Degree of pollution	3

## Electrical properties

Rated voltage (II/2)	320 V
Rated voltage (III/2)	160 V
Rated voltage (III/3)	160 V
Nominal voltage ATD	160
Rated surge voltage	2.5 kV
	2.5 kV
Rated current	10 A
	10 A

### Connection data

Connection method	PCB connection
Connection method	1 OD CONNECTION

### Dimensions

Dimensional drawing	2.4 20.71 15 15 15 15 15 15 15 15 15 15 15 15 15
Width	15 mm
Height	23.1 mm
Length	28.6 mm
Hole diameter	1.2 mm

### Material specifications

Color	light grey
-------	------------



1884885

https://www.phoenixcontact.com/us/products/1884885

Color of the housing part	gray
Material Housing	PA
Material Contact carrier	PA 6.6
Material Contact	CuMg
Flammability rating according to UL 94	V0
Contact surface material	tin-plated

## Mechanical properties

hanica	

Insertion/withdrawal cycles	> 100	
insertion/withdrawar cycles	≥ 100	

### Environmental and real-life conditions

### Ambient conditions

1884885

https://www.phoenixcontact.com/us/products/1884885



## Drawings

Dimensional drawing

2,4

20,71

15

988


5,4

11,06

2,25

10,5

Drilling plan/solder pad geometry





https://www.phoenixcontact.com/us/products/1884885



## **Approvals**

To download certificates, visit the product detail page: https://www.phoenixcontact.com/us/products/1884885

7/	<b>UL Recognized</b> Approval ID: E118976				
		Nominal voltage U <sub>N</sub>	Nominal current I <sub>N</sub>	Cross section AWG	Cross section mm <sup>2</sup>
keine					
		250 V	8 A	-	-



1884885

https://www.phoenixcontact.com/us/products/1884885

## Classifications

UNSPSC 21.0

### **ECLASS**

	ECLASS-13.0	27440192			
	ECLASS-15.0	27440192			
ETIM					
	ETIM 9.0	EC002943			
UNSPSC					

39121400



https://www.phoenixcontact.com/us/products/1884885



## Environmental product compliance

#### EU RoHS

Fulfills EU RoHS substance requirements	Yes, No exemptions			
China RoHS				
Environment friendly use period (EFUP)	EFUP-E			
	No hazardous substances above the limits			
EU REACH SVHC				
REACH candidate substance (CAS No.)	No substance above 0.1 wt%			

Phoenix Contact 2025 @ - all rights reserved https://www.phoenixcontact.com

Phoenix Contact USA 586 Fulling Mill Road Middletown, PA 17057, United States (+717) 944-1300 info@phoenixcon.com