

1337851

https://www.phoenixcontact.com/us/products/1337851

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Safe extension module with 4 safe analog inputs, 0 V ... 10 V; 0 mA or 4 mA ... 20 mA; TBUS interface, up to Cat. 4/PL e, SIL 3, plug-in Push-in terminal block, TBUS connector included

## Product description

The configurable and individually scalable PSRmodular safety system is a flexible safety solution for monitoring your machine or system. The safe extension module provides the system with additional safe analog inputs.

#### Your advantages

- · Cost-effective safety solution with a high level of adaptability to individual requirements
- · Fast startup, thanks to easy hardware and software configuration
- · Machine downtimes minimized with comprehensive, easy-to-understand diagnostics
- · Tool-free and time-saving installation thanks to Push-in technology
- · Low housing width of just 22.6 mm
- Up to Cat. 4/PL e in accordance with ISO 13849-1, SIL 3 in accordance with EN IEC 62061, SIL 3 in accordance with IEC 61508
- Suitable for elevator applications in accordance with EN 81-20
- · Corrosion protection through protective coating on the PCB
- Suitable for ATEX Zone 2 or Class I Zone 2

#### Commercial data

Item number	1337851
Packing unit	1 pc
Minimum order quantity	1 pc
Sales key	DN02
Product key	DNA362
GTIN	4063151639730
Weight per piece (including packing)	192.5 g
Weight per piece (excluding packing)	159 g
Customs tariff number	85371098
Country of origin	IT



1337851

https://www.phoenixcontact.com/us/products/1337851

## Technical data

### Product properties

Product type	Safety device
Application	Analog IN
Control	1 and 2 channel
Insulation characteristics	
Protection class	III
Insulation characteristics	
Overvoltage category	II
Degree of pollution	2
Times	
Response time	see user manual
Restart time	min. 5 s (Boot time)
	max. 10 s (Boot time)

## Electrical properties

Maximum power dissipation for nominal condition	2.76 W (with max. permissible load)
Nominal operating mode	100% operating factor
Interfaces	DIN rail TBUS for connection to the master module, supplied as standard
Rated surge voltage/insulation	Basic insulation 4 kV between all current paths and housing
	Electrical isolation, 0.5 kV functional insulation between logic and analog inputs and between the analog inputs

#### Supply

Designation	A1/A2
Rated control circuit supply voltage U <sub>S</sub>	19.2 V DC 28.8 V DC
Rated control circuit supply voltage $U_S$	24 V DC -20 % / +20 % (external fuse, typically 6 A)
Rated control supply current I <sub>S</sub>	typ. 82 mA (without sensor supply)
	typ. 212 mA (with sensor supply)
Power consumption at U <sub>S</sub>	typ. 1.96 W (without sensor supply)
	typ. 5.08 W (with sensor supply)
Inrush current	max. 14 A ( $\Delta t = 1$ ms at U <sub>s</sub> )
Filter time	typ. 5 ms (in the event of voltage dips at $U_s$ )
Protective circuit	Serial protection against polarity reversal

### Input data

#### Analog

Allalog	
Input name	IN S1, IN S2, IN S3, IN S4
Description of the input	Safety-oriented analog inputs, configurable as current or voltage inputs, galvanically isolated
Number of inputs	4



1337851

https://www.phoenixcontact.com/us/products/1337851

Connection technology	2-conductor, 3-conductor or 4-conductor (2-conductor sensor signal + 2-conductor sensor supply)
Note regarding the connection technology	shielded
Scanning rate	2.5/5/10/16.6/20/50/60/100/200/400/800/1000/2000/4000 Hz
Current input signal	0 mA 25 mA (Measuring range)
	0 mA 20 mA (Configurable measuring range with diagnostics range 20.1 mA 23 mA)
	4 mA 20 mA (Configurable measuring range with diagnostics range 20.1 mA 23 mA (upper limit), 2.5 mA 3.8 mA (lower limit))
Voltage input signal	0 V 12 V (Measuring range)
	0 V 10 V (Configurable measuring range with diagnostics range 10.05 V 11.5 V (upper limit), 0.1 V (lower limit))
Max. permissible current	max. 35 mA (as current input)
Permissible voltage	max. 24 V (as current input)
	max. 14 V (as voltage input)
Input resistance current input	290 $\Omega$ ±25 % (incl. internal protective circuit)
Input resistance of voltage input	185 kΩ ±25 %
A/D converter resolution	16 bit
Resolution (current)	381 nA
Resolution (voltage)	152 µV
Precision	typ. ± 2 % (as current input, relative to the measuring range fina value)
	max. ± 2.5 % (as current input)
	typ. ± 1 % (as voltage input, relative to the measuring range fina value)
	max. ± 1.5 % (as voltage input)
Temperature coefficients	typ. ± 0.07 %/K
	max. ± 0.07 %/K
Limit frequency (3 dB)	160 Hz (RC low pass, 1st order, as current input)
	4 Hz (RC low pass, as voltage input)
Frequency	20 Hz (max. recommended sensor signal frequency, as current input)
	2 Hz (max. recommended sensor signal frequency, as voltage input)
Permissible cable length	max. 100 m (per input)
Protective circuit	Overload protection of the current inputs
	Overload protection of the voltage inputs

## Output data

Sensor supply: OUT S1/0V ...OUT S4/0V

Description	Sensor supply voltage per analog input
Supply voltage	24 V DC ±3 %
Current	max. 30 mA (Sensor current recording per channel)
Short-circuit-proof	yes
Protective circuit	Overload protection Overload detection at ≥ 💴 🕯 mA



1337851

https://www.phoenixcontact.com/us/products/1337851

### Connection data

Connection technology	
pluggable	yes
Conductor connection	
Connection method	Push-in connection
Conductor cross-section rigid	0.2 mm² 2.5 mm²
Conductor cross-section flexible	0.2 mm² 2.5 mm²
Conductor cross-section AWG	24 14
Stripping length	10 mm
Signaling	
Status display	4 x LED (yellow, red)
Operating voltage display	1 x LED (green)
Dimensions	
Width	22.61 mm
Height	107.74 mm
Depth	113.6 mm
Material specifications	
Color (Housing)	yellow (RAL 1018)
Housing material	Polyamide PA non-reinforced
Characteristics	
Safety data	
Stop category	0
Safety data: EN ISO 13849	
Performance level (PL)	e (2-channel wiring)
	d (1-channel wiring)
Safety data: IEC 61508 - High-demand for 2-channel wiring	
Safety Integrity Level (SIL)	3
Safety data: IEC 61508 - High-demand for 1-channel wiring	
Safety Integrity Level (SIL)	2
Safety data	
Safety Integrity Level (SIL)	2
Safety data: EN IEC 62061	
Safety Integrity Level (SIL)	3 (2-channel wiring)
	2 (1-channel wiring)

#### Environmental and real-life conditions



1337851

https://www.phoenixcontact.com/us/products/1337851

#### Ambient conditions

Degree of protection	IP20
Min. degree of protection of inst. location	IP54
Ambient temperature (operation)	-10 °C 70 °C (observe derating)
Ambient temperature (operation) (ATEX)	-10 °C 50 °C (When used in potentially explosive areas. Observe derating)
Ambient temperature (storage/transport)	-20 °C 85 °C
Maximum altitude	≤ 2000 m (Above sea level)
Max. permissible humidity (storage/transport)	95 % (non-condensing)
Max. permissible relative humidity (operation)	95 % (non-condensing)
Shock	10g for $\Delta t$ = 16 ms (continuous shock, 1000 shocks in each space direction)
Vibration (operation)	10 Hz 150 Hz, 2g

## Approvals

Note	T4: for -10°C ≤ T <sub>amb</sub> ≤ <b>®</b> . <b>⊕∜</b> °C
UL Ex, USA / Canada	
Identification	Class I, Div. 2, Groups A, B, C, D T4
Note	T4: for -10°C ≤ T <sub>amb</sub> ≤ <b>®</b> .⊕ <b>∜</b> °C
CE	
Identification	CE-compliant
Environmental simulation test	
Identification	G3
Certificate	ISA-S71.04

### Mounting

Mounting type	DIN rail mounting
Assembly note	Observe derating
Mounting position	vertical or horizontal



1337851

https://www.phoenixcontact.com/us/products/1337851

## **Approvals**

To download certificates, visit the product detail page: https://www.phoenixcontact.com/us/products/1337851



cULus Listed

Approval ID: E238705



**cULus Listed**Approval ID: E196811



1337851

https://www.phoenixcontact.com/us/products/1337851

## Classifications

UNSPSC 21.0

#### **ECLASS**

ECLASS-13.0	27371819
ECLASS-15.0	27371819
ECLASS-15.0 ASSET	27250101
ETIM	
ETIM 9.0	EC001449
UNSPSC	

39122200



1337851

https://www.phoenixcontact.com/us/products/1337851

## Environmental product compliance

#### EU RoHS

Fulfills EU RoHS substance requirements	Yes, No exemptions
China RoHS	
Environment friendly use period (EFUP)	EFUP-E
	No hazardous substances above the limits
EU REACH SVHC	
REACH candidate substance (CAS No.)	No substance above 0.1 wt%

Phoenix Contact 2025 @ - all rights reserved https://www.phoenixcontact.com

Phoenix Contact USA 586 Fulling Mill Road Middletown, PA 17057, United States (+717) 944-1300 info@phoenixcon.com