SIEMENS

Data sheet 3RF2350-1AA45



Solid-state contactor 1-phase 3RF2 AC 51 / 50 A / 40 $^{\circ}\text{C}$ 48-600 V / 4-30 V DC screw terminal Blocking voltage 1200 V

product brand name	SIRIUS
product designation	solid-state contactor
design of the product	1-pole
product type designation	3RF23
manufacturer's article number	
 1 of the accessories that can be ordered 	3RF2900-3PA88
 _3 of the accessories that can be ordered 	3RF2900-0EA18
 _4 of the accessories that can be ordered 	3RF2950-0GA16
product designation	
 _1 of the accessories that can be ordered 	terminal cover
 _3 of the accessories that can be ordered 	converter
_4 of the accessories that can be ordered	load monitoring
General technical data	
product function	zero-point switching
power loss [W] for rated value of the current	
 at AC in hot operating state 	54 W
 at AC in hot operating state per pole 	54 W
 without load current share typical 	0.6 W
insulation voltage rated value	600 V
degree of pollution	3
surge voltage resistance of main circuit rated value	6 kV
protection class IP	IP20
protection class IP on the front according to IEC 60529	IP20
shock resistance according to IEC 60068-2-27	15g / 11 ms
vibration resistance according to IEC 60068-2-6	2g
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	05/28/2009
SVHC substance name	Lead - 7439-92-1 Lead monoxide (lead oxide) - 1317-36-8 Dibutylbis(pentane-2,4-dionato-O,O')tin - 22673-19-4
Net Weight	0.45 kg
Main circuit	
number of poles for main current circuit	1
number of NO contacts for main contacts	1
number of NC contacts for main contacts	0
type of voltage of the operating voltage	AC
operating voltage	
• at AC	
— at 50 Hz rated value	48 600 V
— at 60 Hz rated value	48 600 V

anausting fraguency rated walva	50 G0 Hz
operating range relative to the operating voltage at AC	50 60 Hz
operating range relative to the operating voltage at AC	40 600 V
• at 50 Hz	40 660 V
• at 60 Hz	40 660 V
operational current	
• at AC-1 at 400 V rated value	50 A
• at AC-51 rated value	50 A
at AC-51 according to IEC 60947-4-3	36 A
according to UL 508 rated value	45 A
rate of voltage rise at the thyristor for main contacts maximum permissible	1 000 V/μs
blocking voltage at the thyristor for main contacts maximum permissible	1 200 V
reverse current of the thyristor	10 mA
derating temperature	40 °C
surge current resistance rated value	1 150 A
I2t value maximum	6 600 A²-s
Control circuit/ Control	
type of voltage of the control supply voltage	DC
control supply voltage 1 at DC rated value maximum permissible	30 V
control supply voltage 1 at DC	4 30 V
control supply voltage	
at DC initial value for signal <1> detection	4 V
at DC full-scale value for signal<0> recognition	1 V
control current at minimum control supply voltage	
at DC	18 mA
control current at DC rated value	20 mA
ON-delay time	1 ms; additionally max, one half-wave
OFF-delay time	1 ms; additionally max. one half-wave
Auxiliany circuit	
Auxiliary circuit	
number of CO contacts for auxiliary contacts	0
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions	
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting	Yes
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals 2x (1.5 2.5 mm²), 2x (2.5 6 mm²)
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — finely stranded with core end processing	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals 2x (1.5 2.5 mm²), 2x (2.5 6 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm²
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — finely stranded with core end processing • for AWG cables for main contacts	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals 2x (1.5 2.5 mm²), 2x (2.5 6 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm²
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — finely stranded with core end processing • for AWG cables for main contacts connectable conductor cross-section for main contacts • solid or stranded	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals 2x (1.5 2.5 mm²), 2x (2.5 6 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm² 2x (14 10)
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — finely stranded with core end processing • for AWG cables for main contacts connectable conductor cross-section for main contacts • solid or stranded • finely stranded with core end processing	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals 2x (1.5 2.5 mm²), 2x (2.5 6 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm² 2x (14 10) 1.5 6 mm²
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — finely stranded with core end processing • for AWG cables for main contacts connectable conductor cross-section for main contacts • solid or stranded • finely stranded with core end processing type of connectable conductor cross-sections	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals 2x (1.5 2.5 mm²), 2x (2.5 6 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm² 2x (14 10) 1.5 6 mm²
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit type of connectable conductor cross-sections • for main contacts — solid — finely stranded with core end processing • for AWG cables for main contacts connectable conductor cross-section for main contacts • solid or stranded • finely stranded with core end processing type of connectable conductor cross-sections • for auxiliary and control contacts	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals $2x (1.5 2.5 mm^2), 2x (2.5 6 mm^2)$ $2x (1 2.5 mm^2), 2x (2.5 6 mm^2), 1x 10 mm^2$ $2x (14 10) 1.5 6 mm^2 1 10 mm^2$
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals 2x (1.5 2.5 mm²), 2x (2.5 6 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm² 2x (14 10) 1.5 6 mm² 1 10 mm²
number of CO contacts for auxiliary contacts Installation/ mounting/ dimensions fastening method side-by-side mounting fastening method design of the thread of the screw for securing the equipment height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection	Yes screw fixing and snap-on mounting on standard mounting rail 35 mm according to IEC 60715 M4 100 mm 67 mm 141 mm Yes screw-type terminals screw-type terminals $2x (1.5 2.5 mm^2), 2x (2.5 6 mm^2)$ $2x (1 2.5 mm^2), 2x (2.5 6 mm^2), 1x 10 mm^2$ $2x (14 10) 1.5 6 mm^2 1 10 mm^2$

 for AWG cables for auxiliary and control contacts 	1x (20 12)
AWG number as coded connectable conductor cross section for main contacts	10 14
tightening torque	
 for main contacts with screw-type terminals 	2 2.5 N·m
 for auxiliary and control contacts with screw-type terminals 	0.5 0.6 N·m
tightening torque [lbf·in]	
 for main contacts with screw-type terminals 	18 22 lbf·in
 for auxiliary and control contacts with screw-type terminals 	4.5 5.3 lbf·in
design of the thread of the connection screw	
for main contacts	M4
 of the auxiliary and control contacts 	M3
stripped length of the cable	
• for main contacts	10 mm
 for auxiliary and control contacts 	7 mm
Electrical Safety	
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
Ambient conditions	
installation altitude at height above sea level maximum	1 000 m
ambient temperature	
during operation	-25 +60 °C
during storage	-55 +80 °C
Electromagnetic compatibility	
conducted interference	
 due to burst according to IEC 61000-4-4 	2 kV / 5 kHz behavior criterion 2
due to conductor-earth surge according to IEC 61000-4-5	2 kV behavior criterion 2
 due to conductor-conductor surge according to IEC 61000-4-5 	1 kV behavior criterion 2
 due to high-frequency radiation according to IEC 61000- 4-6 	140 dBuV in the frequency range 0.15 80 MHz, behavior criterion 1
field-based interference according to IEC 61000-4-3	80 MHz 1 GHz 10 V/m, behavior criterion 1
electrostatic discharge according to IEC 61000-4-2	4 kV contact discharging / 8 kV air discharging, behavior criterion 2
conducted HF interference emissions according to CISPR11	Class A for industrial environment
field-bound HF interference emission according to CISPR11	Class B for the domestic, business and commercial environments
Short-circuit protection, design of the fuse link	
manufacturer's article number	
 of gS fuse for semiconductor protection at NH design usable 	<u>3NE1817-0</u>
 of full range R fuse link for semiconductor protection at cylindrical design usable 	<u>5SE1363</u>
 of back-up R fuse link for semiconductor protection at NH design usable 	<u>3NE1817-0</u>
 of back-up R fuse link for semiconductor protection at cylindrical design 14 x 51 mm usable 	<u>3NC1450</u>
 of back-up R fuse link for semiconductor protection at cylindrical design 22 x 58 mm usable 	<u>3NC2280</u>
manufacturer's article number	
of NEOZED fuse usable	5SE2335; These fuses have a smaller rated current than the semiconductor relays
last modified:	8/3/2025 🗗