SIEMENS

Data sheet

6EP4132-0GB00-0AY0

SITOP UPS1100/Battery module/24V/2.5AH

SITOP UPS1100 battery module with maintenance- free sealed pure lead-acid for SITOP DC UPS modules 24 V DC 2.5 Ah



Technical Product Detail Page	https://i.siemens.com/1P6EP4132-0GB00-0AY0	
electrical data		
end-of-charge voltage at DC		
• at -10 °C recommended	28 V	
• at 0 °C recommended	28 V	
• at 10 °C recommended	27.8 V	
 at 20 °C recommended 	27.3 V	
 at 30 °C recommended 	26.8 V	
 at 40 °C recommended 	26.6 V	
 at 50 °C recommended 	26.3 V	
 at 60 °C recommended 	26 V	
output		
battery capacity	2.5 A·h	
output current rated value	20 A	
output current in buffering mode maximum	20 A	
peak current	60 A; for 30 ms	
charging current maximum	5 A	
output voltage at DC rated value	24 V	
interfaces		
communication function	Yes	
protection and monitoring		
design of short-circuit protection	Battery fuse 25 A/32 V (solid-state circuitry blade-type fuse + support)	
design of the overload protection	Valve control	
display version for normal operation	LED green: Battery OK; LED flashing green: Error or warning; OFF: No communication	
safety		
operating resource protection class	Class III	
protection class IP	IP20	
standards, specifications, approvals		
certificate of suitability		
CE marking	Yes	
 UL approval 	Yes; cURus-Recognized (UL 1778, CSA C22.2 No. 107.1), File E219627	
 EAC approval 	Yes	
standards, specifications, approvals hazardous environments		
certificate of suitability		
• ATEX	No	
standards, specifications, approvals marine classification		
shipbuilding approval	Yes	
Marine classification association		

 American Bureau of Shipping Europe Ltd. (ABS) 	Yes	
Det Norske Veritas (DNV)	Yes	
standards, specifications, approvals Environmental Product De	claration	
Environmental Product Declaration	Yes	
global warming potential [CO2 eq]		
• total	13.68 kg	
 during manufacturing 	9.127 kg	
 during operation 	2.917 kg	
after end of life	0.481 kg	
ambient conditions		
ambient condition	For storage, mounting and operation of lead-acid batteries, the relevant DIN/VDE regulations or country-specific regulations (e.g. VDE 0510 Part 2/EN 50272-2) must be observed. You must ensure that the battery site is sufficiently ventilated. Possible sources of ignition must be at least 50 cm away.	
ambient temperature		
 during operation 	-40 +60 °C	
 during transport 	-40 +60 °C	
during storage	-40 +60 °C	
relative temporary capacity loss at 20 °C in a month typical	3 %	
service life		
service life of energy storage		
• typical	capacity falls to 80 % of original capacity (according to EUROBAT)	
• at 20 °C typical	10 a	
• at 30 °C typical	7 a	
• at 40 °C typical	3 a	
• at 50 °C typical	1.5 a	
• at 60 °C typical	1 a	
note	Along with the storage and operating temperature, other factors such as the duration of the storage period and the charge status during storage have a decisive influence on the possible useful life. Batteries should therefore be stored as briefly as possible, always fully charged, and within the temperature range 0 to +20 °C.	
connection method		
type of electrical connection	screw terminal	
	screw terminal 1 screw terminal each for 0.2 6 mm² for + BAT and - BAT	
type of electrical connection		
type of electrical connection • for UPS module	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm²	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm	
type of electrical connection • for UPS module • for control circuit and status message mechanical data width × height × depth of the enclosure installation width × mounting height required spacing • top • bottom • left	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35×7.5/15 or keyhole mounting for hooking in to	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg 12	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg 12	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg 12	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg 12 Accessories pack with solid-state circuitry fuse 25 A	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg 12 Accessories pack with solid-state circuitry fuse 25 A https://mall.industry.siemens.com https://www.siemens.com/tstcloud	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg 12 Accessories pack with solid-state circuitry fuse 25 A https://mall.industry.siemens.com/tstcloud https://www.siemens.com/tstcloud https://siemens.com/sitop	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg 12 Accessories pack with solid-state circuitry fuse 25 A https://mall.industry.siemens.com https://www.siemens.com/tstcloud	
type of electrical connection	1 screw terminal each for 0.2 6 mm² for + BAT and - BAT 1 screw terminal each for 0.14 4 mm² 265 × 115 × 76 mm 265 mm × 130 mm 15 mm 0 mm 0 mm 0 mm 0 mm snaps onto DIN rail EN 60715 35x7.5/15 or keyhole mounting for hooking in to M4 screws Yes No Yes 3.7 kg 12 Accessories pack with solid-state circuitry fuse 25 A https://mall.industry.siemens.com/tstcloud https://www.siemens.com/sitop https://www.siemens.com/cax	

other information

Specifications at rated input voltage and ambient temperature +25 °C (unless otherwise specified)

security information

security information

Siemens provides products and solutions with industrial cybersecurity functions that support the secure operation of plants, systems, machines and networks. In order to protect plants, systems, machines and networks against cyber threats, it is necessary to implement – and continuously maintain – a holistic, state-of-the-art industrial cybersecurity concept. Siemens' products and solutions constitute one element of such a concept. Customers are responsible for preventing unauthorized access to their plants, systems, machines and networks. Such systems, machines and components should only be connected to an enterprise network or the internet if and to the extent such a connection is necessary and only when appropriate security measures (e.g. firewalls and/or network segmentation) are in place. For additional information on industrial cybersecurity measures that may be implemented, please visit www.siemens.com/cybersecurity-industry. Siemens' products and solutions undergo continuous development to make them more secure. Siemens strongly recommends that product updates are applied as soon as they are available and that the latest product versions are used. Use of product versions that are no longer supported, and failure to apply the latest updates may increase customer's exposure to cyber threats. To stay informed about product updates, subscribe to the Siemens Industrial Cybersecurity RSS Feed under https://www.siemens.com/cert. (V4.7)

Classifications

	Version	Classification
eClass	14	27-05-04-03
eClass	12	27-05-04-03
eClass	9.1	27-05-04-03
eClass	9	27-05-04-03
eClass	8	27-05-04-03
eClass	7.1	27-05-04-03
eClass	6	27-05-04-90
ETIM	10	EC000357
ETIM	9	EC000357
ETIM	8	EC000357
ETIM	7	EC000357
UNSPSC	15	26-11-17-01

Approvals Certificates

General Product Approval

Maritime application

Manufacturer Declaration

Declaration of Conformity









Maritime application

Dangerous goods

Environment



Dangerous goods information



last modified:

11/25/2025