

LCCA30369-FT1



Configuration

- Connector 1: SMA Male Right Angle
- Connector 2: SMA Female
- Cable Type: RG223

Features

- Max Frequency 12.4 GHz
- 66% Phase Velocity

Applications

· General Purpose

- · Double Shielded
- PVC Jacket

· Laboratory Use



Description

L-com's LCCA30369-FT1 is a SMA male right angle to SMA female cable assembly using RG223 coax, 1 FT and ships same-day. The RG223 coax of this SMA cable uses the PE dielectric with a VoP of 66%. These flexible RF cable assemblies are ideal for applications where flexure is required. Our L-com SMA to SMA cable assembly has a male to female gender configuration with flexible RG223 series coax and operates to 12.4 GHz. The double shield of this SMA cable is layered by silver plated copper braid over silver plated copper braid. This right angle SMA cable interface on the RG223 coax allows for easier connections in tight spaces.

Custom versions of this SMA male to SMA female cable, along with the rest of L-com's other RF assemblies, can also be built and shipped same day. Other available RF cable assembly value added services from L-com include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly. Contact a sales representative for testing or custom RF cable quotes. Part number LCCA30369-FT1 L-com SMA Male Right Angle to SMA Female Cable Assembly using RG223 Coax, 1 FT data sheet PDF includes details of the RF product specifications, CAD drawing(s) and dimensions below.





LCCA30369-FT1

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		12.4	GHz
VSWR			1.5:1	
Velocity of Propagation		66		%
Capacitance		30.8 [101.05]		pF/ft [pF/m]
Operating Voltage (AC)			500	Vrms

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.5	1	2.5	5	11	GHz
Insertion Loss (Typ.)	0.4	0.44	0.5	0.64	0.85	dB

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in the assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB for the straight connector and 0.2 dB for the right angle connector.

0.209 in [5.31 mm]

Mechanical Specifications

Cable Assembly

Jacket Diameter

 Length
 12 in [304.8 mm]

 Diameter
 0.315 in [8 mm]

 Weight
 0.062 lbs [28.12 g]

Cable

RG223 Cable Type Impedance 50 Ohms Inner Conductor Type Solid Inner Conductor Material and Plating Copper, Silver Dielectric Type PΕ Number of Shields Silver Plated Copper Braid Shield Layer 1 Silver Plated Copper Braid Shield Layer 2 Jacket Material PVC, Black

One Time Minimum Bend Radius 0.984 in [24.99 mm]
Repeated Minimum Bend Radius 1 in [25.4 mm]



LCCA30369-FT1

Connectors

Description	Connector 1	Connector 2		
Туре	SMA Male Right Angle	SMA Female		
Specification	MIL-STD-348A			
Impedance	50 Ohms	50 Ohms		
Contact Material and Plating	Brass, Gold	Beryllium Copper, Gold		
Contact Plating Specification	50μ in. minimum	50μ in. minimum.		
Dielectric Type	Teflon	PTFE		
Body Material and Plating	Brass, Nickel	Brass, Nickel		
Body Plating Specification	100μ in. minimum	100μ in. minimum.		
Coupling Nut Material and Plating	Brass, Nickel			
Coupling Nut Plating Specification	100μ in. minimum			
Hex Size	5/16 in			
Torque	3 in-lbs 0.34 Nm			

Compliance Certifications (see product page for current document)

Plotted and Other Data


Notes:



LCCA30369-FT1



How to Order



Example: LCCA30369-12 = 12 inches long cable

LCCA30369-100cm = 100 cm long cable

SMA Male Right Angle to SMA Female Cable Assembly using RG223 Coax, 1 FT from L-com has same day shipment for domestic and International orders. L-com is a leading manufacturer of wired and wireless connectivity products and committed to in-stock availability and same day shipping. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components.

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.ontained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

L-com CAD Drawing

