

# FMC00472-36 DATA SHEET

# Low Loss SMA Male to RA SMA Male Cable LMR-240 Coax in 36 Inch

The SMA male to RA SMA male 36 inch cable using LMR-240 coax, part number FMC00472-36, from Fairview Microwave is in-stock and ships same day. This Fairview SMA to SMA cable assembly has a male to male gender configuration with 50 ohm flexible LMR-240 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00472-36 SMA male to SMA male cable assembly operates to 5.8 GHz. The right angle SMA interface on the LMR-240 cable allows for easier connections in tight spaces. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

## **Electrical Specifications**

Description	Min	Т	ур	Max	ι	Jnits	
Frequency Range	DC			5.8		GHz	
VSWR				1.4:1			
Velocity of Propagation		8	34			%	
RF Shielding	90					dB	
Group Delay		1.21	[3.97]		ns/f	t [ns/n	n]
Capacitance		24.2	[79.4]		pF/f	t [pF/n	n]
Inductance		0.06	[0.2]		uH/f	t [uH/r	n]
DC Resistance Inner Cor	ductor	3.2	[10.5]		Ω/100	Oft [Ω/I	Km]
DC Resistance Outer Conductor		3.89	[12.76]		Ω/100	Oft [Ω/I	Km]
Dielectric Withstanding \	/oltage (DC)			1,000		Vdc	
Jacket Spark				5,000	\	/rms	
Input Power (Peak)				5.6	K	Watts	

### **Performance by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	5.8	GHz
Insertion Loss (Typ.)	0.37	0.42	0.49	0.64	0.87	dB

### **Electrical Specification Notes:**

The Insertion Loss data above is based on the performance specifications of the coax and connectors used in this assembly. The Insertion Loss includes an estimated 0.15 dB for the right angle connector and 0.1 dB for the straight connector.

## **Mechanical Specifications**

## **Cable Assembly**

Length\* Diameter 36 in [914.4 mm] 0.24 in [6.1 mm]



## **Configuration:**

- SMA Male
- SMA Male Right Angle
- LMR-240

## Features:

- Max Frequency 5.8 GHz
- Shielding Effectivity > 90 dB
- 84% Phase Velocity
- Double Shielded
- PE Jacket

## **Applications:**

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com

sales@fairviewmicrowave.com





0.032 lbs [14.51 g] Weight

Cable

Cable Type LMR-240 50 Ohms **Impedance** Inner Conductor Type Solid Inner Conductor Material and Plating Copper PE (F)

Dielectric Type Number of Shields 2 Shield Layer 1 Aluminum Tape Shield Layer 2 Tinned Copper Braid PE, Black

Jacket Material

Jacket Diameter

One Time Minimum Bend Radius Repeated Minimum Bend Radius

Bending Moment Flat Plate Crush Tensile Strength

0.24 in [6.1 mm] 0.75 in [19.05 mm] 2.5 in [63.5 mm]

0.25 lbs-ft [0.34 N-m] 20 lbs/in [0.36 Kg/mm] 80 lbs [36.29 Kg]

#### **Connectors**

Description	Connector 1	Connector 2
Туре	SMA Male	SMA Male
Specification	MIL-STD-348	MIL-STD-348
Impedance	50 Ohms	50 Ohms
Mating Cycles		500
Contact Material & Plating	Beryllium Copper, G	old Brass/Phosphor Bronze, Gold
Contact Plating Spec.	ASTM B488	50 μinch
Dielectric Type	PTFE	PTFE
Outer Cond Material & Plati	ing Passivated Stainless Ste	el, Gold
Body Material & Plating	Passivated Stainless Ste	el, Gold Brass, Tri-Metal
Body Plating Spec.	SAE-AMS-2700	80 µinch
Coupling Nut Material & Pla	ting Passivated Stainless S	Steel Brass, Tri-Metal
Coupling Nut Plating Spec.	SAE-AMS-2700	80 µinch
Hex Size		5/16 inch
Torque		7 in-lbs 0.79 Nm
Seal Gasket Material	Silicone Rubber	Silicone

# **Environmental Specifications**

**Temperature** 

Operating Range -40 to +85 deg C Storage Range -70 to +85 deg C

**Compliance Certifications** (see product page for current document)

## **Plotted and Other Data**

Notes:

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2020





## **How to Order**

Part Number Configuration:	FMC00472	- xx	uu	
				cm = Centimeters <blank> = Inches Length</blank>

Example: FMC00472-12 = 12 inches long cable

FMC00472-100cm = 100 cm long cable

Low Loss SMA Male to RA SMA Male Cable LMR-240 Coax in 36 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: Low Loss SMA Male to RA SMA Male Cable LMR-240 Coax in 36 Inch FMC00472-36

URL: https://www.fairviewmicrowave.com/sma-male-ra-sma-male-cable-Imr240-coax-fmc00472-36-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





