

RA SMA Male to N Female Bulkhead Cable RG316 Coax in 120 Inch

The RA SMA male to type N female bulkhead 120 inch cable using RG-316 coax, part number FMC0411315-120, from Fairview Microwave is in-stock and ships same day. This Fairview SMA to type N cable assembly has a male to female gender configuration with 50 ohm flexible RG316 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC0411315-120 SMA male to type N female cable assembly operates to 3 GHz. The right angle SMA interface on the RG316 cable allows for easier connections in tight spaces. Our RF cable assembly with type N bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	T	yp N	1ax U	Inits
Frequency Range	DC			3	GHz
Velocity of Propagation		7	70		%
Capacitance		32 [1	04.99]	pF/f	t [pF/m]

FMC0411315-120 DATA SHEET



Configuration:

- SMA Male Right Angle
- N Female Bulkhead
- RG316

Features:

- Max Frequency 3 GHz
- 70% Phase Velocity
- FEP Jacket

Applications:

- General Purpose
- Laboratory Use

Mechanical Specifications

Cable Assembly

Length*

Weight

Cable

Cable Type Impedance

Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type
Number of Shields
Shield Layer 1
Shield Layer 2
Jacket Material

Jacket Diameter

120 in [304.8 cm] 0.199 lbs [90.26 g]

RG316 50 Ohms Solid Copper, Silver PTFE

Silver Plated Copper Tape Silver Plated Copper Braid

FEP, Black

0.098 in [2.49 mm]

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Connectors

Description	Connector 1	Connector 2		
Туре	SMA Male	N Female		
Mount Method		Bulkhead		
Impedance	50 Ohms	50 Ohms		
Contact Material & Plating	Brass, Gold	Beryllium Copper, Gold		
Contact Plating Spec.	50μ in. minimum	30µ in. minimum		
Dielectric Type	Teflon	Teflon		
Body Material & Plating	Brass, Nickel	Brass, Nickel		
Body Plating Spec.	100μ in. minimum	n 100µ in. minimum		
Hex Size	5/16 inch	3/4 inch		

Environmental Specifications

Part Number Configuration:

Temperature

Operating Range

-65 to +165 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

FMC0411315 - xx uu | cm = Centimeters | cblank > = Inches

Length

Example: FMC0411315-12 = 12 inches long cable

FMC0411315-100cm = 100 cm long cable

RA SMA Male to N Female Bulkhead Cable RG316 Coax in 120 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: RA SMA Male to N Female Bulkhead Cable RG316 Coax in 120 Inch FMC0411315-120

URL: https://www.fairviewmicrowave.com/ra-sma-male-n-female-cable-rg316-coax-fmc0411315-120-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





