ABC.00.250.NTM





Image for illustrative purpose only

Summary

Request a quote

Catalog

Nb of contacts Coax	1	
Locking system	Push-pull	
Size	00	
Suggested matching part	FFA.00.250.NTAC22	
Series	00 - NIM-CAMAC	

Technical details

Electrical Configuration

Nb of contacts Coax	1	
Contact Termination Coax - Conductor fixing	Crimp	
Insert configuration value	00.250/ABC - 1 Coax (50 Ohm)	
Insulator	T: PTFE	
Rated current	4 A	
Impedance	50 Ohms	
VSWR	1.09 + 0.11 * f/GHz	
Vtest	2100 V (AC), 3000 V (DC)	
Contact retention	18 N	
Contact Dia.	0.7 mm (0.03in)	
Form & Material		
Shell style / Model id	ABC - Adapter from LEMO receptacle to BNC receptacle	
Housing material	Brass (nickel plated [SAE AMS QQ N 290]) shell, collet nut, latch sleeve and mid pieces	
Locking system	Push-pull	
Keying	Circular, female	
Colour	Grey	
Weight	16.92 g	
Environment		
Environmental sealing (IP rating)	IP50	
Endurance	>1000 mating cycles	
Temperature range	-55°C / +260°C (max. temperature valid for short periods of use.)	
F ret (min)	100 N	
Salt Spray Corrosion	>144 hr	
Cable fixation		
Cable termination protection	Standard back nut (no additional protection)	

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Drawings



Dimensions

	A	L
mm.	14.5	29.5
in.	0.57	1.16

Recommended By Lemo

Tools

Crimp tool

DPC.91.701.V