



INTEL® FPGA PROGRAMMABLE ACCELERATION CARD (INTEL FPGA PAC)

FEATURES		INTEL PAC WITH INTEL ARRIA® 10 GX FPGA	INTEL FPGA PAC N3000	INTEL FPGA PAC D5005
Physical Dimension	Width	Single slot	Single slot	Dual slot
	Form Factor	½ length, full height	½ length, full height	¾ length, Full height
		½ length, ½ height		
Weight	255 g	364 g	1,000 g	
Memory	DDR Format	8 GB DDR4 SDRAM	4 GB DDR4 SDRAM	8 GB DDR4 SDRAM (RDIMM)
	DDR Total Capacity	16 GB	9 GB	32 GB
	DDR Maximum Data Rate	2400 MT/s	2400 MT/s	2400 MT/s
	QSPI Flash Memory	1 Gb	2 Gb	2 Gb
	SRAM Total Capacity	-	144 Mb QDR IV	-
Interfaces and Modules	PCI Express*	Gen 3x8 (electrical)	Gen 3x16	Gen 3x16
		Gen 3x16 (mechanical)		
	Network Interface	1 x QSFP+	2 x QSFP28	2 x QSFP28
	USB Interface	USB 2.0	-	USB 2.0
	Dual Intel Ethernet Converged Network Adapter XL710	No	Yes	No
FPGA Interface Manager	Yes	Yes	Yes	
Power	Typical Power Consumption	45 W	45 W	189 W
	Maximum Power Consumption (TDP)	66 W	100 W	215 W
	Power Management: Intel Enpirion® Power Solutions	Yes	Yes	Yes
FPGA Resources	FPGA	Intel Arria 10 GX	Intel Arria 10 GT	Intel Stratix® 10 SX
	Logic Elements	1,150,000	1,150,000	2,753,000
	Adaptive Logic Modules (ALMs) Registers	1,708,800	1,708,800	3,732,480
	On-chip Memory	65.7 Mb	65.7 Mb	244 Mb
	DSP Blocks	3,036	3,036	11,520
Tools Support	Intel Acceleration Stack for Intel Xeon® CPU with FPGAs	Yes	Yes	Yes
	Intel Quartus® Prime Software	Yes	Yes	Yes
	Open Programmable Acceleration Engine (OPAE)	Yes	Yes	Yes
	Data Plane Developer Kit (DPDK)	-	Yes	-
	Intel Distribution of OpenVINO™ Toolkit	Yes	-	-

All information provided here is subject to change without notice. Features and benefits of Intel's technologies depend on system configuration, hardware, software and services. Intel, the Intel logo, the Intel Inside mark and logo, the Intel. Experience What's Inside mark and logo, Altera, Arria, Enpirion, Intel, Intel Core, Intel Xeon, MAX, Nios, Quartus and Stratix are trademarks of Intel Corporation or its subsidiaries in the U.S. and/or other countries.

*Other names and brands may be claimed as the property of others
Copyright © Intel Corporation, All Rights Reserved